

Secto Design Oy
Kauppalantie 12
02700 Kauniainen
Finland
tel. +358 9 5050598
fax +358 9 5475 2535
info@sectodesign.fi
www.sectodesign.fi

Secto Design



Atto 5000 pendant

natural birch, black laminate or white laminate, walnut veneer.

- The shade is made of form pressed birch slats
- White and black finishes have been laminated
- Walnut finish has a waxed walnut veneer on top
- Height of the shade 21 cm, diameter 34 cm, weight 1,9 kg
- The cable is a heat-resistant textile cable, standard length 180 cm, comes with a ceiling plug and a ceiling cup
- Light source (included): LED, 13 W, 3000 K, 800 lm, dimmable (trailing edge). Also available with 2700 K
- International Protection Rating: IP20
- Dimension of the box: 39 x 39 x 30 cm, 3 kg

Secto Design recommends the use of the following Trailing edge type of dimmers with the LED ATTO 5000:

Manufacturer	Dimmer	Note	Minimum LED-Load	Minimum Dim-range	Stability
BERKER	286710	Sam as Insta 51190	2.5 Watt	20%	OK
BERKER	-	Same as Insta 53128R	-	25%	NOT
BUSCH J	6513U-102		7.5 Watt	20%	OK
ELARI	ATD 315		2.5 Watt	20%	OK
ELARI	ADT 600R		7.5 Watt	20%	OK
EPV	PAB 315		2.5 Watt	20%	OK
GIRA	-	Same as Insta 51190	2.5 Watt	20%	OK
GIRA	-	Same as Insta 53128R	-	25%	NOT
INSTA	51190		2.5 Watt	20%	OK
INSTA	53128 R		-	25%	NOT
INSTA	FUNK 576650 22		10 Watt	30%	OK
INSTA	51040		2.5 Watt	20%	OK
JUNG	1254 UDE	Same as Insta 53128R	-	25%	NOT
JUNG	225TDE		2.5 Watt	20%	OK
LUTRON	LPRPM-4A		2.5 Watt	15%	OK
LUTRON	GRAFIK INTEGRAL GXI		2.5 Watt	15%	OK
OPUS	852395		2.5 Watt	30%	OK
PEHA	433HAB		2.5 Watt	20%	OK
SCHNEIDER	ATD 315		2.5 Watt	20%	OK
SCHNEIDER	600R		7.5 Watt	20%	OK
SIEMENS	5 TC8 284		7.5 Watt	15%	OK

(An overview of the Trailing-edge dimmers that are tested with the L05021 MINIDIM Driver)

20.08.2014 Secto Design Oy



Dezell Installation

Svenska

dezell lamptops

Tight fit guaranteed

Dezell® Lamptops är ett nytt och enkelt sätt att hänga upp lampor. Lamptoppen monteras på befintlig sladd och kräver inte att sladden kapas.
Så här gör du:



Lås fast sladden i den övre delen av skruven, börja med mittenhålet. Lägg sedan in sladden inuti gångan. Tryck ned den ordentligt i botten. Finns en gammal kåpa kan denna tas bort från sladden genom att tex. klippa den i två bitar och placera ringen mot taket ovanpå kåpan.



Trä in skruven, kontakt och överbliven sladd genom kåpan underifrån. Trä även genom ringen om denna ska användas för att få en större kåpa, eller då kontakten till taklampa sitter en bit ifrån där lampan ska hänga. Tryck då ut ett av de förberedda hålen, låt sladden löpa därigenom och placera ringen mot taket ovanpå kåpan.



De två matchande bottendelarna läggs nu runt sladden, mot varandra, mellan kåpan och lampan. Tryck ihop dem ordentligt. För in botten i kåpan genom att passa i bottendelens "vingar" i spären inuti kåpan. Tryck in botten tills dess att ytan underrill blir helt plan.



Häng upp skruven på takkroken och sätt i kontakten (eller kopplingsplinten). Se först till att takkroken sitter fast i taket och inte roterar. Häng på krogen, samla ihop den överblivna sladden och vira denna runt den övre delen av skruven/kroken (undvik dock själva gångan). Fäst med bifogad fästråd.



För lamptoppen uppåt mot skruven som hänger på krogen. När skruv och botten-delens "mutter" har hittat varandra inne i kåpan kan man börja skriva lamptoppen medslols uppåt. Skruva tills toppen når taket. För att hitta rätt kan du försiktigt dra i sladden nedåt, då kommer skruven automatiskt att vinklas rakt nedåt och därmed lätt hitta in i bottendelen.



Lamptoppen sitter nu perfekt mot taket.



www.dezell.se

Dezell Installation

English

dezell lamptops

Tight fit guaranteed


Dezell® Lamptops is a new and simple way to mount lamps. The lamptop is mounted onto the existing cord and doesn't require the cord to be cut or to make screwholes in the ceiling.
This is how it works:



Lock the cord in the upper part of the screw, start in the middle. Then insert it into the opening along the thread. Push it down into the bottom of the channel. If there is an old cover, this can be removed from the cord e.g. by cutting it with scissors.




Insert the screw, plug and remaining cord through the cover from below. Also insert it through the ring if this is to be used. The ring can be used to make the cover bigger, or if the outlet for the ceiling lamp is located at a distance from where the lamp is to be placed. Push out a perforated tab to make room for the cord and place the ring to the ceiling on top of the cover.



Put the two matching bottom parts together, facing each other, around the cord between the cover and the lamp. Insert the assembled bottom part into the cover by fitting the "wings" into the slots inside the cover. Push it into the cover until fully seated.



Hang the screw on the ceiling hook and connect the plug. (or terminal block). First ensure that the ceiling hook is fixed to the ceiling and does not rotate. When connected, collect the remaining cord, wind it around the upper part of the screw and hook and tie it up using the enclosed wire-tie (avoid winding it around the thread).



Move the lamptop upwards towards the screw hanging on the hook. When the screw and the bottom parts' "nut" have come in contact inside the cover, start screwing the cover clockwise until it reaches the ceiling. By pulling the cord lightly from below, the screw will automatically be angled downwards and will then easily find the nut.



The lamptop is now sitting straight to the ceiling.



www.dezell.se

SECTO DESIGN ATTO 5000



This luminaire contains built-in LED lamps.



L
E
D

A large blue curly brace is positioned to the left of the letters 'LED', grouping them together.

The LED lamps cant be changed in the luminaire.

